

EN LED WIFI smart RGB strip for TV, 4x50cm, USB Solight WM58

Dear customer, thank you for purchasing our product. Please read the following instructions carefully and follow them to serve you safely and to your full satisfaction. This may prevent misuse or damage. Avoid unprofessional handling of this appliance and always observe the electrical appliance usage guidelines. Keep the instruction manual carefully.

Notice

- Avoid placing the luminaire near objects that are sources of heat or moisture.
- Do not look directly at a lit luminaire for long periods of time as this may cause discomfort or damage to your eyes.
- Do not expose the luminaire to the outdoors, direct rain or immerse it in water. The luminaire is intended for indoor use.
- Periodically wipe the luminaire with a dry or damp cloth only when the luminaire is unplugged.

Parameters

	Belt	Driver
Power	USB 5V, 1200mA	Battery CR2032 3 V
Power	6 W; max. 260 lm/m	
Operating temperature	-20 °C ~ +60 °C	
Controller range	5 m	

Installation

The LED strip is suitable for TVs with 32-65" (80-165cm) screen. Install the strip according to the pictures below depending on the diagonal size of the TV.



Package contents:

IR 24 Keys



4x 50cm LED strip, 1x wifi module, 1x remote control,
1x power cable, 3x flexible connector, 3x fixed connectors

Remote control functions:

Symbol	Key Note	Symbol	Key Note	Symbol	Key Note	Symbol	Key Note
	Brightness +		Jas -		Turn off		Turn on
	Static red		Static green		Static blue		Static white
	Static orange		Static pea green		Static dark blue		Flicker 1
	Static dark yellow		Static cyan		Static brown		Flicker 2
	Static yellow		Static light blue		Static Pink		Fading - 3 colours
	Static straw yellow		Static sky blue		Static purple		Colour gradients - 7 colours

CONTROL VIA APP

Download and install the Smart Life app



STEP 1 Search Google Play or the App Store for and install the Smart Life apps.

STEP 2 Register a new account using your email or phone number and log in to the app

STEP 3 Switch to pairing mode

In order to pair the luminaire with the Smart Life app, it needs to be switched to pairing mode. This is indicated by flashing and is activated by plugging and unplugging the luminaire 4 times in succession. After the fourth plugging, you need to wait a few seconds and the strip will flash.

STEP 4 Add a device

Launch the Smartlife app and tap the "+" button in the top right corner -> Lighting -> Lights (Wi-Fi). Then enter the login details of the wifi network your phone is currently connected to and tap "Next". On the next screen, confirm by tapping "Confirm the light is blinking rapidly;" that the light is blinking rapidly and then tap "Next". The pairing process takes a while. After successful pairing, the device will appear in the overview on the main screen of the app.

STEP 4 Tap the device to control it according to the functions offered by the app you downloaded, e.g. the Smart Life app mentioned above.

You can find the video guide on Youtube by searching for the term *solight led smart wifi* or scan the QR code

Note: The lights can only be connected to 2.4GHz WIFI.

The product is covered by a declaration of conformity in accordance with the applicable regulations. On request from the manufacturer: info@solight.cz, or downloadable from www.solight.cz. This product contains a light source which for design reasons cannot be removed for verification and therefore the whole product is considered to be a light source.

Producer: Solight Holding, s.r.o., Na Brně 1972, Hradec Králové 500 06, Czech Republic

CE IP20



Smart
LifeGoogle



Smart Life
App Store

